

Wels, March 23th 2021

DECLARATION OF CONFORMITY WITH “TECHNICAL REQUIREMENTS FOR CONNECTION OF POWER GENERATING PLANTS TO THE LOW VOLTAGE GRID (≤ 1 KV); VERSION 1.1 (DEC. 2019)”

Manufactures Name	Fronius International GmbH
Manufacturer Address	Froniusplatz 1 4600 Wels Austria
Name of Contact Person	Bernhard Kossak, MSc
Contact Person's telephone number	+43 (7242) 241 4691
Contact Person's Email address	Kossak.Bernhard@fronius.com

Fronius Hereby confirms that the inverters listed in the following table fulfill the requirements of “

“*Technical requirements for connection of power generating plants to the low voltage grid (≤ 1 kV); Version 1.1 (Dec 2019)*” published by Dansk Energi.

Model designation	Model software version	Nominal active power [kW]	Number of phases
Fronius Primo 3.0-1	0.3.25.0	3.0	1
Fronius Primo 3.5-1	0.3.25.0	3.5	1
Fronius Primo 3.6-1	0.3.25.0	3.6	1
Fronius Symo 3.0-3-S	0.3.25.0	3.0	3
Fronius Symo 3.7-3-S	0.3.25.0	3.7	3
Fronius Symo 4.5-3-S	0.3.25.0	4.5	3
Fronius Symo 3.0-3-M	0.3.25.0	3.0	3
Fronius Symo 3.7-3-M	0.3.25.0	3.7	3
Fronius Symo 4.5-3-M	0.3.25.0	4.5	3
Fronius Symo 5.0-3-M	0.3.25.0	5.0	3
Fronius Symo 6.0-3-M	0.3.25.0	6.0	3
Fronius Symo 7.0-3-M	0.3.25.0	7.0	3
Fronius Symo 8.2-3-M	0.3.25.0	8.2	3
Fronius Symo 10.0-3-M	0.3.25.0	10.0	3
Fronius Symo 12.5-3-M	0.3.25.0	12.5	3
Fronius Symo 15.0-3-M	0.3.25.0	15.0	3
Fronius Symo 17.5-3-M	0.3.25.0	17.5	3
Fronius Symo 20.0-3-M	0.3.25.0	20.0	3
Fronius Symo Hybrid 3.0-3-S	1.16.6.1	3.0	3
Fronius Symo Hybrid 4.0-3-S	1.16.6.1	4.0	3
Fronius Symo Hybrid 5.0-3-S	1.16.6.1	5.0	3
Fronius Eco 25.0-3-S	0.3.25.0	25.0	3
Fronius Eco 27.0-3-S	0.3.25.0	27.0	3



Model designation	Model software version	Nominal active power [kW]	Number of phases
Fronius Primo GEN24 3.0	1.11.6.0	3.0	1
Fronius Primo GEN24 3.6	1.11.6.0	3.68	1
Fronius Primo GEN24 4.0	1.11.6.0	4.0	1
Fronius Primo GEN24 4.6	1.11.6.0	4.6	1
Fronius Primo GEN24 5.0	1.11.6.0	5.0	1
Fronius Primo GEN24 6.0	1.11.6.0	3.0	1
Fronius Primo GEN24 Plus 3.0	1.11.6.0	3.0	1
Fronius Primo GEN24 Plus 3.6	1.11.6.0	3.68	1
Fronius Primo GEN24 Plus 4.0	1.11.6.0	4.0	1
Fronius Primo GEN24 Plus 4.6	1.11.6.0	4.6	1
Fronius Primo GEN24 Plus 5.0	1.11.6.0	5.0	1
Fronius Primo GEN24 Plus 6.0	1.11.6.0	3.0	1
Fronius Symo GEN24 3.0	1.11.6.0	3.0	3
Fronius Symo GEN24 4.0	1.11.6.0	4.0	3
Fronius Symo GEN24 5.0	1.11.6.0	5.0	3
Fronius Symo GEN24 6.0	1.11.6.0	6.0	3
Fronius Symo GEN24 8.0	1.11.6.0	8.0	3
Fronius Symo GEN24 10.0	1.11.6.0	10.0	3
Fronius Symo GEN24 Plus 3.0	1.11.6.0	3.0	3
Fronius Symo GEN24 Plus 4.0	1.11.6.0	4.0	3
Fronius Symo GEN24 Plus 5.0	1.11.6.0	5.0	3
Fronius Symo GEN24 Plus 6.0	1.11.6.0	6.0	3
Fronius Symo GEN24 Plus 8.0	1.11.6.0	8.0	3
Fronius Symo GEN24 Plus 10.0	1.11.6.0	10.0	3
Fronius Tauro 50-3-D	1.11.6.0	50.0	3
Fronius Tauro 50-3-P	1.11.6.0	50.0	3
Fronius Tauro Eco 50-3-D	1.11.6.0	50.0	3
Fronius Tauro Eco 50-3-P	1.11.6.0	50.0	3
Fronius Tauro Eco 99-3-D	1.11.6.0	99.99	3
Fronius Tauro Eco 99-3-P	1.11.6.0	99.99	3
Fronius Tauro Eco 100-3-D	1.11.6.0	100.0	3
Fronius Tauro Eco 100-3-P	1.11.6.0	100.0	3

The following setting are configured in the Setups DKA1 and DKA2:

Parameter	DKA1	DKA2
LFSM-O		
Threshold frequency [Hz]	50.2	50.5
Drop [% of P_n]	5 % (40 % P_n /Hz)	4 % (50 % P_n /Hz)
Intentional Delay [ms]	500	500
Reactive Power		
Q fix		
Enabled/Disabled [On/Off]	On	On
Q setpoint [VAr]	0	0
Cos φ fix		
Enabled/Disabled [On/Off]	Off	Off
Power factor setpoint	1	1
Cos φ (P)		
Enabled/Disabled [On/Off]	Off	Off
Cos φ (P) P1 [% of P_n]	0	0
Cos φ (P) Power factor at P1	1	1
Cos φ (P) P2 [% of P_n]	50	50
Cos φ (P) Power factor at P2	1	1
Cos φ (P) P3 [% of P_n]	100	100
Cos φ (P) Power factor at P3	0.9 inductive	0,9 inductive
Cos φ (P) Lockin [% of U_n]	105	105
Cos φ (P) Lockout [% of U_n]	100	100
Connection and Reconnection		
Softstart Gradient [% of P_n /min]	20	20
Observation time [s]	180	180
U_{min} [% of U_n]	85	85
U_{max} [% of U_n]	110	110
f_{min} [Hz]	47.5	47.5
f_{max} [Hz]	50.2	50.5
System Protection		
$f >$ [s]	0.2	0.2
$f >$ [Hz]	51.5	51.5
$f <$ [s]	0.2	0.2
$f <$ [Hz]	47.5	47.5
$U >$ [s]	60	60
$U >$ [% of U_n]	110	110
$U >>$ [s]	0.2	0.2
$U >>$ [% of U_n]	115	115
$U <$ [s]	50	50
$U <$ [% of U_n]	85	85
Loss of Mains Detection		
$U <<$ [s]	0.2	0.2
$U <<$ [% of U_n]	80	80
RoCoF [s]	0.08	0.08
RoCoF [Hz/s]	2.5	2.5



Fronius International GmbH
Business Unit Solar Energy
Froniusplatz 1
A-4600 Wels

A handwritten signature in blue ink that reads "Bernhard Kossak".

Bernhard Kossak, MSc
Head of Systems Technology