


# SELECTIVA FIRMWARE UPDATE

## SYSTEM REQUIREMENTS FOR USB FLASH DRIVE:

- / Max. 32 Gb
- / FAT32 formatting
- / No external hard drive
- / Only one partition

## DOWNLOAD FROM WEBSITE:

<http://www.fronius.com> ▶ Download Search ▶ search for „Firmware“



Choose „Perfect Charging“ category ► Download „Update Package Selectiva“

Home ► Download Search

### FIND YOUR DOWNLOADS HERE

firmware 🔍

**FRONIUS** 0 | **PERFECT WELDING** 20 | **SOLAR ENERGY** 48 | **PERFECT CHARGING** 8

#### FILTER

**Languages** ▼  
☐ DE  
☐ EN

**Relevant country** ▼

#### DOWNLOADS (8)

Format	Document type	Title	Languages	Size
	Firmware	Installation guidelines Selectiva Update	EN	70,7 KB
	Firmware	Update Package Selectiva	DE, EN	2 MB
	Firmware	Acctiva Professional Flash Firmware		28,7 KB
	Firmware	Firmware Active Inverter		2,2 MB

Save on USB flash drive ► Unpack the zip-file in the root directory (main directory)

Computer

- Lokaler Datenträger (C:)
- Wechseldatenträger (F:)**

Name

- BCS\_FW\_Selectiva3P\_MULTI
- BCS\_FW\_Selectiva3P\_MULTI.zip

Rename the unzipped folder to „FRONIUS“ ► Safely remove the USB flash drive ►  
Connect the USB flash drive to the Selectiva-Charger

Name

- BCS\_FW\_Selectiva\_MULTI.ZIP
- FRONIUS**

Änderungsdatum

- 24.10.2017
- 25.10.2017

## INSTALLATION ON THE UNIT:


Connect the USB flash drive to the Selectiva-Charger ► Menu opens automatically

Use the arrow buttons to navigate to update ► Select by pressing Start/Stop button ►

Update starts ► After the Update is installed "Update successful" is shown on the display ►

Confirm by pressing Start/Stop button

Update should not be interrupted, e.g. by cutting off the AC supply.



Choose and confirm the menu item "safely remove" within the USB menu

Note: Only if there is an update file on the USB stick, the menu item "Update" is shown and can be selected.

Troubleshooting: Menu doesn't open by itself

Press Menu button for 5 sec. ► Menu opens



Use the arrow buttons to navigate to the USB-Symbol ►

Select by pressing Start/Stop button



/ Perfect Welding / Solar Energy / Perfect Charging

### WE HAVE THREE DIVISIONS AND ONE PASSION: SHIFTING THE LIMITS OF POSSIBILITY.

/ Whether welding technology, photovoltaics or battery charging technology – our goal is clearly defined: to be the innovation leader. With around 3,800 employees worldwide, we shift the limits of what's possible - our record of over 1,200 granted patents is testimony to this. While others progress step by step, we innovate in leaps and bounds. Just as we've always done. The responsible use of our resources forms the basis of our corporate policy.

Further information about all Fronius products and our global sales partners and representatives can be found at [www.fronius.com](http://www.fronius.com)

v07 Apr 2017 EN