



ENA Engineering Recommendation G99 Issue 1 – Amendment 4 2018

FORM A2-3 Compliance Verification Report for Inverter Connected Power Generating Modules

This form should be used by the **Manufacturer** to demonstrate and declare compliance with the requirements of EREC G99. The form can be used in a variety of ways as detailed below:

1. To obtain Fully Type Tested status

The **Manufacturer** can use this form to obtain **Fully Type Tested** status for a **Power Generating Module** by registering this completed form with the Energy Networks Association (ENA) Type Test Verification Report Register.

Note:


Within this Form A2-3 the term Power Park Module will be used but its meaning can be interpreted within Form A2-3 to mean Power Park Module, Generating Unit or Inverter as appropriate for the context. However, note that compliance must be demonstrated at the Power Park Module level.

If the Power Generating Module is Fully Type Tested and registered with the Energy Networks Association (ENA) Type Test Verification Report Register, the Installation Document (Form A3) should include the Manufacturer's reference number (the Product ID), and this form does not need to be submitted.

Where the Power Generating Module is not registered with the ENA Type Test Verification Report Register or is not Fully Type Tested this form (all or in parts as applicable) needs to be completed and provided to the DNO, to confirm that the Power Generating Module has been tested to satisfy all or part of the requirements of this EREC G99.

Manufacturer's reference number		Fronius Eco 27.0-3-S	
PGM technology		IGBT power modules, transformerless	
Manufacturer name		Fronius International GmbH	
Adress		Guenther Fronius Str. 1 4600 Wels-Thalheim, Austria	
Tel	+43-7242-241-0	Fax	+43-7242-241-224
E:mail	pv@fronius.com	Web site	www.fronius.com
Registered Capacity		27.0kW	

Manufacturer compliance declaration. - I certify that all products supplied by the company with the above **Type Tested Manufacturer's** reference number will be manufactured and tested to ensure that they perform as stated in this document, prior to shipment to site and that no site **Modifications** are required to ensure that the product meets all the requirements of EREC G99.

Signed		On behalf of	Fronius International GmbH
--------	---	--------------	----------------------------

Note that testing can be done by the **Manufacturer** of an individual component or by an external test house.

Where parts of the testing are carried out by persons or organisations other than the **Manufacturer** then that person or organisation shall keep copies of all test records and results supplied to them to verify that the testing has been carried out by people with sufficient technical competency to carry out the tests.



ENA Engineering Recommendation G99 Issue 1 – Amendment 4 2018

<p>1. Operating Range: Five tests should be carried with the Power Generating Module operating at Registered Capacity and connected to a suitable test supply or grid simulation set. The power supplied by the primary source shall be kept stable within $\pm 5\%$ of the apparent power value set for the entire duration of each test sequence.</p> <p>Frequency, voltage and Active Power measurements at the output terminals of the Power Generating Module shall be recorded every second. The tests will verify that the Power Generating Module can operate within the required ranges for the specified period of time.</p> <p>The Interface Protection shall be disabled during the tests.</p> <p>In case of a PV Power Park Module the PV primary source may be replaced by a DC source. In case of a full converter Power Park Module (eg wind) the primary source and the prime mover Inverter/rectifier may be replaced by a DC source.</p>
<p>Test 1</p> <p>Voltage = 85% of nominal (195.5 V) Frequency = 47.0 Hz Power factor = 1 Period of test 20 s</p>
<p>Test 2</p> <p>Voltage = 85% of nominal (195.5 V). Frequency = 47.5 Hz Power factor = 1 Period of test 90 minutes</p>
<p>Test 3</p> <p>Voltage = 110% of nominal (253 V). Frequency = 51.5 Hz Power factor = 1 Period of test 90 minutes</p>
<p>Test 4</p> <p>Voltage = 110% of nominal (253 V). Frequency = 52.0 Hz Power factor = 1 Period of test 15 minutes</p>
<p>Test 5 RoCoF withstand</p> <p>Confirm that the Power Generating Module is capable of staying connected to the Distribution Network and operate at rates of change of frequency up to 1 Hzs^{-1} as measured over a period of 500 ms. Note that this is not expected to be demonstrated on site.</p>
<p><u>Remark:</u> No disconnection</p>

2. Power Quality – Harmonics:

For **Power Generating Modules** of **Registered Capacity** of less than 75 A per phase (ie 50 kW) the test requirements are specified in Annex A.7.1.5. These tests should be carried out as specified in BS EN 61000-3-12 The results need to comply with the limits of Table 2 of BS EN 61000-3-12 for single phase equipment and Table 3 of BS EN 61000-3-12 for three phase equipment.

Power Generating Modules with emissions close to the limits laid down in BS EN 61000-3-12 may require the installation of a transformer between 2 and 4 times the rating of the **Power Generating Module** in order to accept the connection to a **Distribution Network**.

For **Power Generating Modules** of **Registered Capacity** of greater than 75 A per phase (ie 50 kW) the installation shall be designed in accordance with EREC G5.

Power Generating Module rating per phase (rpp)			9 kVA		Harmonic % = Measured Value (A) x 23/rating per phase (kVA)	
Harmonic	At 45-55% of Registered Capacity		100% of Registered Capacity		Limit in BS EN 61000-3-12	
	Measured Value MV in Amps	%	Measured Value MV in Amps	%	1 Phase	3 phase
2	0.048	0.122	0.042	0.107	8%	8%
3	0.049	0.124	0.077	0.197	21.6%	Not stated
4	0.047	0.120	0.047	0.120	4%	4%
5	0.075	0.193	0.186	0.476	10.7%	10.7%
6	0.024	0.062	0.020	0.051	2.67%	2.67%
7	0.045	0.116	0.081	0.207	7.2%	7.2%
8	0.037	0.094	0.036	0.091	2%	2%
9	0.040	0.101	0.060	0.153	3.8%	Not stated
10	0.026	0.067	0.029	0.075	1.6%	1.6%
11	0.032	0.082	0.042	0.106	3.1%	3.1%
12	0.017	0.043	0.018	0.045	1.33%	1.33%
13	0.047	0.121	0.061	0.157	2%	2%
THD ¹²	0.15	0.73	0.24	0.6	23%	13%
PWHD ¹³	0.24	1.22	0.27	0.7	23%	22%

¹² THD = Total Harmonic Distortion

¹³ PWHD = Partial Weighted Harmonic Distortion

3. Power Quality – Voltage fluctuations and Flicker:

For **Power Generating Modules of Registered Capacity** of less than 75 A per phase (ie 50 kW) these tests should be undertaken in accordance with Annex A.7.1.4.3. Results should be normalised to a standard source impedance, or if this results in figures above the limits set in BS EN 61000-3-11 to a suitable Maximum Impedance.

For **Power Generating Modules of Registered Capacity** of greater than 75 A per phase (ie 50 kW) the installation must be designed in accordance with EREC P28.

	Starting			Stopping			Running	
	d_{max}	d_c	$d_{(t)}$	d_{max}	d_c	$d_{(t)}$	P_{st}	P_{it} 2 hours
Measured Values at test impedance	0.42%	0.52%	-	0.48%	0.47%	-	0.079	0.096783
Normalised to standard impedance	0.42%	0.52%	-	0.48%	0.47%	-	0.079	0.096783
Normalised to required maximum impedance	-	-	-	-	-	-	-	-
Limits set under BS EN 61000-3-11	4%	3.3%	3.3%	4%	3.3%	3.3%	1.0	0.65
Test Impedance	R	0.24	Ω	X	0.15	Ω		
Standard Impedance	R	0.24 * 0.4 [^]	Ω	X	0.15 * 0.25 [^]	Ω		
Maximum Impedance	R	-	Ω	X	-	Ω		

* Applies to three phase and split single phase **Power Generating Modules**.

[^] Applies to single phase **Power Generating Module** and **Power Generating Modules** using two phases on a three phase system.

For voltage change and flicker measurements the following formula is to be used to convert the measured values to the normalised values where the power factor of the generation output is 0.98 or above.

Normalised value = Measured value*reference source resistance/measured source resistance at test point.

Single phase units reference source resistance is 0.4 Ω

Two phase units in a three phase system reference source resistance is 0.4 Ω .

Two phase units in a split phase system reference source resistance is 0.24 Ω .

Three phase units reference source resistance is 0.24 Ω .

Where the power factor of the output is under 0.98 then the X to R ratio of the test impedance should be close to that of the Standard Impedance.

The stopping test should be a trip from full load operation.



ENA Engineering Recommendation G99 Issue 1 – Amendment 4 2018

MATERIALS & SAFETY - R&D

TR 28361

page 5 of 8

The duration of these tests need to conform to the particular requirements set out in the testing notes for the technology under test. Dates and location of the test need to be noted below.

Test start		Test end	
Test location	Fronius R&D Laboratories, Fronius International GmbH, Guenter Fronius Str 1, A-4600 Wels-Thalheim, Austria		

4. Power quality – DC injection: The tests should be carried out on a single **Generating Unit**. Tests are to be carried out at three defined power levels $\pm 5\%$. At 230 V a 50 kW three phase **Inverter** has a current output of 217 A so DC limit is 543 mA. These tests should be undertaken in accordance with Annex A.7.1.4.4.

Test power level	10%	55%	100%
Recorded value in Amps	0.0116A	0.0172A	0.0317A
as % of rated AC current	0.029%	0.043%	0.081%
Limit	0.25%	0.25%	0.25%

5. Power Factor: The tests should be carried out on a single **Power Generating Module**. Tests are to be carried out at three voltage levels and at **Registered Capacity**. Voltage to be maintained within $\pm 1.5\%$ of the stated level during the test. These tests should be undertaken in accordance with Annex A.7.1.4.2.

Voltage	0.94 pu (216.2 V)	1 pu (230 V)	1.1 pu (253 V)
Measured value	1.00	1.00	1.00
Power Factor Limit	>0.95	>0.95	>0.95

6. Protection – Frequency tests: These tests should be carried out in accordance with Annex A.7.1.2.3.

Function	Setting		Trip test		"No trip tests"	
	Frequency	Time delay	Frequency	Time delay	Frequency /time	Confirm no trip
U/F stage 1	47.5Hz	20s	47.490Hz	20.380s	47.7Hz 30s	Confirmed
U/F stage 2	47Hz	0.5s	46.990Hz	0.536s	47.2Hz 19.5s	Confirmed
					46.8Hz 0.45s	Confirmed
O/F stage 1	52Hz	0.5s	52.005Hz	0.537s	51.8Hz 120.0s	Confirmed
					52.2Hz 0.45s	Confirmed

Note. For frequency trip tests the frequency required to trip is the setting ± 0.1 Hz. In order to measure the time delay a larger deviation than the minimum required to operate the projection can be used. The "No trip tests" need to be carried out at the setting ± 0.2 Hz and for the relevant times as shown in the table above to ensure that the protection will not trip in error.



ENA Engineering Recommendation G99 Issue 1 – Amendment 4 2018

MATERIALS & SAFETY - R&D

TR 28361

page 6 of 8

7. Protection – Voltage tests: These tests should be carried out in accordance with Annex A.7.1.2.2.

Function	Setting		Trip test		"No trip tests"	
	Voltage	Time delay	Voltage	Time delay	Voltage /time	Confirm no trip
U/V	0.8 pu (184V)	2.5s	183.03V	2.545s	188V 5.0s	Confirmed
					180V 2.45s	Confirmed
O/V stage 1	1.14 (262.2V)	1.0s	261.52V	1.023s	258.2V 5.0s	Confirmed
O/V stage 2	1.19 (273.7V)	0.5s	274.77V	0.526s	269.7V 0.95s	Confirmed
					277.7V 0.45s	Confirmed

Note for Voltage tests the Voltage required to trip is the setting ± 3.45 V. The time delay can be measured at a larger deviation than the minimum required to operate the protection. The No trip tests need to be carried out at the setting ± 4 V and for the relevant times as shown in the table above to ensure that the protection will not trip in error.

8. Protection – Loss of Mains test: These tests should be carried out in accordance with BS EN 62116. Annex A.7.1.2.4.

The following sub set of tests should be recorded in the following table.

Test Power and imbalance	33% -5% Q Test 22	66% -5% Q Test 12	100% -5% P Test 5	33% +5% Q Test 31	66% +5% Q Test 21	100% +5% P Test 10
Trip time Limit is 0.5s	179.8ms	185.6ms	349.6ms	184.8ms	188ms	283.6ms

Loss of Mains Protection, Vector Shift Stability test. This test should be carried out in accordance with Annex A.7.1.2.6.

	Start Frequency	Change	Confirm no trip
Positive Vector	49.0Hz	+50 degrees	Confirmed
Negative Vector	50.0Hz	-50 degrees	Confirmed

Loss of Mains Protection, RoCoF Stability test: This test should be carried out in accordance with Annex A.7.1.2.6.

Ramp range	Test frequency ramp:	Test Duration	Confirm no trip
49.0 Hz to 51.0Hz	+0.95 Hzs ⁻¹	2.1 s	Confirmed
51.0 Hz to 49.0Hz	-0.95 Hzs ⁻¹	2.1 s	Confirmed

9. Limited Frequency Sensitive Mode – Over frequency test: The test should be carried out using the specific threshold frequency of 50.4 Hz and **Droop** of 10%.

This test should be carried out in accordance with Annex A.7.1.3.

Active Power response to rising frequency/time plots are attached if Y/N

Frequency injection tests are undertaken in accordance with Annex A.7.2.4.

Alternatively, simulation results should be noted below:

Test sequence at Registered Capacity >80%	Measured Active Power Output	Frequency	Primary Power Source	Active Power Gradient
Step a) 50.00 Hz ±0.01 Hz	27030W	50,00Hz	32kW	20%/Hz
Step b) 50.45 Hz ±0.05 Hz	26790W	50,45Hz		
Step c) 50.70 Hz ±0.10 Hz	25460W	50,70Hz		
Step d) 51.15 Hz ±0.05 Hz	23054W	51,15Hz		
Step e) 50.70 Hz ±0.10 Hz	25458W	50,70Hz		
Step f) 50.45 Hz ±0.05 Hz	26786W	50,45Hz		
Step g) 50.00 Hz ±0.01 Hz	27006W	50,00Hz		
Test sequence at Registered Capacity 40% - 60%	Measured Active Power Output	Frequency	Primary Power Source	Active Power Gradient
Step a) 50.00 Hz ±0.01 Hz	13633W	50,00Hz	14.5kW	20%/Hz
Step b) 50.45 Hz ±0.05 Hz	13468W	50,45Hz		
Step c) 50.70 Hz ±0.10 Hz	12790W	50,70Hz		
Step d) 51.15 Hz ±0.05 Hz	11576W	51,15Hz		
Step e) 50.70 Hz ±0.10 Hz	12792W	50,70Hz		
Step f) 50.45 Hz ±0.05 Hz	13472W	50,45Hz		
Step g) 50.00 Hz ±0.01 Hz	13640W	50,00Hz		

Steps as defined in EN 50438

10. Protection - Re-connection timer.

Test should prove that the reconnection sequence starts after a minimum delay of 20 s for restoration of voltage and frequency to within the stage 1 settings of Table 10.1.

Time delay setting	Measured delay	Checks on no reconnection when voltage or frequency is brought to just outside stage 1 limits of table 10.1.			
20s	83s	At 1.16 pu (266.2V)	At 0.78 pu (180.0V)	At 47.4Hz	At 52.1Hz
Confirmation that the Power Generation Module does not re-connect.		Confirmed	Confirmed	Confirmed	Confirmed



ENA Engineering Recommendation G99 Issue 1 – Amendment 4 2018

11. Fault level contribution: These tests shall be carried out in accordance with EREC G99 Annex A.7.1.5.		
For inverter output		
Time after fault	Volts	Amps
20 ms	14.5	98.3
100 ms	9.04	44.4
250 ms	7.91	28.9
500 ms	7.51	21.5
Time to trip	0.28	In seconds

12. Self-Monitoring solid state switching: No specified test requirements. Refer to Annex A.7.1.7.	
It has been verified that in the event of the solid state switching device failing to disconnect the Power Park Module , the voltage on the output side of the switching device is reduced to a value below 50 volts within 0.5 s.	NA

13. Wiring functional tests: If required by para 15.2.1.	
Confirm that the relevant test schedule is attached (tests to be undertaken at time of commissioning)	NA

14. Logic interface (input port).	
Confirm that an input port is provided and can be used to shut down the module.	Yes

Additional comments